

CSC-5500

多格式轉 HDMI/VGA 升頻器



產品介紹

本產品為多格式轉 HDMI/VGA 影像升頻器，可將多種數位或類比影音輸入訊號轉換為 HDMI 與電腦或色差等影音輸出訊號，同時將 SD 標準畫質解析度升頻為 HD 高畫質解析度。本產品具有類比轉數位 (ADC) 與數位轉類比 (DAC) 等訊號轉換功能及多項影像處理功能，滿足使用者同時在 HDMI 數位顯示器與 VGA 類比顯示器上選擇播放數位或類比影音來源。而且，本產品內建 OSD 功能選單，提供面板按鈕、紅外線遙控器、RS-232 通訊指令與 Telnet 或 Web GUI 網路控制等多種操作方式，非常適於需要整合 HD 與 SD 影音訊號的安裝環境。

產品特色

- 附有 HDMI 與同軸數位音訊，3.5mm 與 RCA 類比立體聲音訊
- 可切換不同的輸入訊號或快選兩組預設的輸出解析度
- 可自動調整螢幕畫面的最佳位置
- 可設定輸出解析度、畫面尺寸或位置、影像或聲音調校等 OSD 選單功能
- 可設定 HDMI 輸入埠的 HDCP 支援狀態，適於連接 Apple 來源裝置
- 可設定 HDMI 輸出埠的音訊來源，適於連接 DVI 來源裝置
- 可設定影像訊號的雜訊抑制效果
- 可設定聲音訊號的延遲效果
- 支援 HDCP 加密數位影音內容
- 最高支援 WUXGA@60Hz (RB) 或 1080p@60Hz 輸入與輸出解析度
- 支援 NTSC 或 PAL 類比電視訊號系統
- 支援類比或數位輸入音訊嵌入 HDMI 輸出訊號
- 內建類比轉數位 (ADC) 與數位轉類比 (DAC) 等訊號轉換功能

- 內建 3D 去交錯演算法、3D 梳狀濾波器與雜訊抑制等影像處理功能
- 內建畫面更新率轉換與 EDID 資料管理功能
- 支援 RS-232、Telnet、Web GUI 等遠端通訊控制
- 輸出埠 VGA / HDMI 為同步輸出，無法各別獨立輸出



產品規格

Inputs	3x HDMI [3x Uncompressed AV and Data] 3x 15-pin D-sub [3x RGBHV] 6x 3.5mm Stereo Mini-jack [6x Stereo(L/R)] 3x RCA [1x YPbPr Component] 1x RCA [1x Composite Video] 4x RCA [2x Stereo (L/R)] 1x 9-pin D-sub [1x RS-232 Data] 1x 3.5mm Stereo Mini-jack [1x Infrared Receiver] 1x RJ45 [1x IP Control] 1x USB Type A [1x SERVICE Propriety Data]
Outputs	2x HDMI [2x Uncompressed AV and Data] 1x 15-pin D-sub [1x RGBHV / YPbPr Component] 1x RCA [1x COAX 2 Channel LPCM] 1x 3.5mm Stereo Mini-jack [1x Stereo(L/R)]
PSU:	5V/3A
Dimensions	432mm [W] x 183mm [D] x 47mm [H]
Net Weight	2140g